

#### MLD23 Series




# Convergent harnesses for more accurate detection

Akusense has developed its own optical system to significantly converge and improve the beam to 50um;




#### Mini Chinese Display

More Intuitive and Simple for Commissioning



#### Convenient Installation

Integration of analogue voltage, analogue current and switching





#### Micron-level linear accuracy


Linear accuracy reaches to 0.01mm for easy inspection with high accuracy  $% \left( 1\right) =\left( 1\right) \left( 1\right) \left$ 

#### Simple and flexible test patterns

Multiple teaching modes to make testing easier







Fiber Optic

Slot Sensors

Photoelectric

Laser

Displacement

Contact

Ultrasonic

Area

Vision

Code Readers

Vibration

Temperature Accessories

Guidance

Displacement
Triangulation
Linear
measurement

Magnetic displacement LiDAR Scanner Color confocal

### **Selection Guide**


#### **MLD23 Series**

#### Faster, more stable, more accurate

Three test modes are for option: standard, high speed and high accuracy

①Ultra-high speed computing and processing


The application of Akusense 's advanced IC and algorithm technology has greatly improved the sensor's detection rate and data accuracy, allowing for both high speed transmission and stable detection of measured values.






Repeat accuracy up to 10 um

Min ±0.1% F.S linearity






#### 2 Achieving greater precision

The new Akusense high-resolution lens design reduces pixel aberration and is assembled with precision.


The small spot of light at any angle can be imaged at the receiving section, resulting in a smaller waveform and higher measurement accuracy.

### **Application**





### Selection table



Model	MLD23-30N	
Repeat accuracy	10μm	
Linear accuracy	±0.1% F.S.	
Base distance	30mm	
Model	MLD23-100N	
Repeat accuracy	70μm	
Linear accuracy	±0.1% F.S.	
Base distance	100mm	
Model	MLD23-200N	
Repeat accuracy	200μm	
Linear accuracy	±0.2% F.S.	
Base distance	200mm	

Fiber Optic
Slot Sensors
Photoelectric
Laser

Displacement

Magnetic

Contact

Proximity

Ultrasonic

Area

Code Readers

Vibration Temperature

Accessories

Guidance

Displacement

Triangulation

Linear
measurement

Magnetic
displacement

LiDAR Scanner

Color confocal

Fiber Optic Slot Sensors Photoelectric Laser Proximity

Magnetic Contact

Ultrasonic Vision Code Readers Vibration Temperature Accessories



Economical type

Appearance

Principle		Diffuse reflection				
Center of sensing distance		30mm	100mm	200mm		
Sensing distance		25~35mm	65~135mm	120~280mm		
Repeat accuracy		10 µ m	70 µ m	200 µ m		
	Medium, wavelength	Red semiconductor laser, wavelength: 655nm				
Light source	Max. output power	1mW				
	Laser class	Class2				
Standard		EMC				
Temperature drift		±0.03%/°C F.S.				
Spot size		≈ Φ0.05mm	≈ Ф0.15mm	≈ Ф0.3mm		
Linearity		±0.1% F.S.		±0.2% F.S.		
Supply voltage		12~24V DC±10%				
Current consumption		< 60 mA (24V DC), < 100mA (12V DC)				
Response time		1.5ms/5ms/soms switchable				
Switch Output		NPN open-collector transistor, max. inflow current: 50mA; applied voltage: < 3.0V DC (between control output-0V), residual voltage: < 1.5V (inflow current < 50mA)				
Analog output	Voltage	Output range: 0V $\sim$ 5V (when alarm: +5.2V), output impedance: 100 $\Omega$				
	Current	Output range: 4mA $\sim$ 20mA (when alarm: 0mA), load: less than 300 $\Omega$				
External input		Input conditions Invalid: +8V $\sim$ + V DC or open, valid: 0V $\sim$ + 1.2V DC; input impedance: about 10k $\Omega$				
Ambient performance	Protection Degree	IP66				
	Ambient Temperature	-10℃~+45℃, No freezing				
	Ambient humidity	35%~85%RH,No condensation				
	Ambient light	Incandescent lamp: Illumination below 3000Lux on the light-receiving surface				
Cable			5-core 2M cable			
Material		Aluminum, acrylic				
Model		MLD23-30N	MLD23-100N	MLD23-200N		


Guidance


Linear measurement Magnetic displacement LiDAR Scanner Color confocal

Displacement

#### Dimensions


Unit: mm





## **Mini Digital Display**

### Circuit Diagram



Fiber Optic

Slot Sensors

Photoelectric Laser

Proximity

Magnetic

Contact

Area

Ultrasonic

Vision

Code Readers
Vibration

Temperature

Accessories

Guidance

Displacement

Linear measurement Magnetic displacement

LiDAR Scanner Color confocal