

■ PG1 Dual Digital Display Fiber Optic Amplifier


- With automatic light compensation technology, 4-channel anti-light interference
- Small hysteresis, dual output selectable, the fastest speed upto 13 μ s




Model No.	PG1-N HOT	PG1-P
Control output		1 output port
Light source		Red, 4-element LED
Response time	SHP: 13 μ s, FINE: 30 μ s, SUPR: 100 μ s, MEGA: 200 μ s	
Output selection	LIGHT-ON/DARK-ON (Short press MODE and select with UP DOWN)	
Display indicator	Operation indicator: Red LED, dual digital monitor; Dual 7-digit display, threshold (4-digit green LED body indicator) and current value (4-digit red LED body indicator) lit together. Current value range: 0~9999	
Detection method	Light intensity (area detection is available for automatic sensitive tracking)	
Delay function	1ms~9999ms	
Control output	NPN open collector, maximum 100mA, residual voltage: 1V	PNP open collector, maximum 100mA, residual voltage: 1V
Power supply	12~24V DC \pm 10%	
Ambient illuminance	Incandescent lamp \leq 20,000 lux, Sunlight \leq 30000 Lux	
Power consumption	Standard mode: Max 300mW	
Vibration resistance	10~55Hz, double amplitude: 1.5mm, X, Y, Z axis are 2 hours respectively	
Ambient temperature	-10°C~+55°C, No freezing	

Dimensions

Unit: mm



Circuit diagram



Fiber Optic
Slot Sensors
Photoelectric
Laser
Proximity
Displacement
Magnetic
Contact
Area
Ultrasonic
Vision
Vibration
Temperature
Annexes

Guidance
Fiber amplifiers
Standard economical
High stability
High performance type
High speed response
Fiber components
Popular type
Array-type
Flat bracket type
Side-view type
High elastic type
High temperature resistant
Small spot type
Combination type
High end type
Fiber lens
Fiber lens

Highly Stable Type Fiber Amplifier

PG5 Highly Stable Dual Digital Display Fiber Amplifier

- APC compensation function, high stability
- With AI function, automatically configure the most suitable luminous intensity
- Coded menu: greatly reduce the cost of use and maintenance;



Model No.

PG5-N


()

PG5-P

Fiber Optic	light source	Red LED (wavelength 630nm)
Slot Sensors	Reaction time	50μs (P100) , 250μs (P101) , 500μs (P102) , 1ms (P103) ,
Photoelectric	Output method	Normally open and normally closed: L. on, D. on
Laser	Protect the circuit	Power supply reverse connection protection, output surge protection, output reverse connection protection, output overcurrent protection, output ESD protection
Proximity	Timer function	Output off timing, output on timing, output single timing, output timing off
Displacement	Control output	Applied voltage: 30V DC or less (between detection output and 0V) Maximum output current: 100mA; residual voltage: below 2V
Magnetic	Delay function	Conventional: 900mW (at 24V, the maximum is 32mA; at 12V, the maximum is 47mA)
Contact	Timing range	1~9999ms
Area	Utility function	Parameter initialization/key lock/threshold two points, automatic and manual setting, fast saturation attenuation
Ultrasonic	Regional mode	Yes
Vision	voltage	12~24VDC ± 10%
Vibration	Power consumption	20mA max
Temperature	Ambient luminosity	Incandescent lamp: maximum 20000lux, sunlight: maximum 30000lux
Annexes	Ambient temperature	-10°C~+55°C, no freezing
Guidance	Environment humidity	35~85% RH
Fiber amplifiers	Vibration resistance	10 To 55Hz, full width 1.5mm, X, Y, Z axis directions for 2 hours each
Standard economical	Impact resistance	500m/s ² , 3 times each in X, Y, and Z axis directions
High stability	Shell material	Polycarbonate


Dimensions

Unit: mm




Circuit diagram

NPN



PNP



PB1 High Performance Dual Digital Fiber Amplifier

- Infrared communication function
- Regional mode
- 7-speed response time setting
- Novel and unique appearance




Model No.

PB1


Light source	Modulated red light 680nm
Operating voltage	8~30V DC
Saturation voltage	25mA < 1.2V, 100mA < 2V
Load current	< 50mA
Output current	< 200mA
Leakage current	< 100uA
Output type	NPN/PNP open-collector
Switch type	Selectable L.on/D.on
Display screen	7 segment 8 digit display (red: 4 digit, green: 4 digit)
Response time	50 μ s/ 250 μ s/ 500 μ s/ 1ms/ 4ms
Time delay function	< 50ms
Operating temperature	-10°C~+60°C
Operating humidity	35%~85% RH
Ambient brightness	Sunlight≤10000Lux
Protective circuit	Short circuit protection, Reverse polarity protection, Over voltage protection
Shock resistance	10G(1500m/s ²), XYZ three directions
Anti-vibration	10~55Hz Double amplitude 1.5mm, XYZ three directions, 2 hours each
Certification	CE
Connection method	2m 4 wire cable
Weight	65g

Dimensions



Circuit diagram

NPN/PNP



Fiber Optic
Slot Sensors
Photoelectric
Laser
Proximity
Displacement
Magnetic
Contact
Area
Ultrasonic
Vision
Vibration
Temperature
Annexes

Guidance

Fiber amplifiers
Standard economical
High stability
High performance type
High speed response

Fiber components
Popular type
Array-type
Flat bracket type
Side-view type
High elastic type
High temperature resistant
Small spot type
Combination type
High end type

Fiber lens
Fiber lens

PC1 Ultra High Speed Response Dual Digital Display Fiber Amplifier


- Fastest response time in the industry (15ms)
- Digital display of red and green light in comparison, easy installation
- Unique technology for light compensation, stable detection



Model No.	PC1-NH	PC1-NH2	PC1-PH	PC1-PH2
Light source		Red LED 660nm		
Operating voltage		12~24V DC		
No-load supply current		Standard mode: 36mA max.(Single output)、39mA max.(Double output) Energy-saving mode: 25mA max.(Single output), 28mA max.(Double output)		
Output type	Single output NPN ≤100mA / 30V DC, Load current≤100mA, Voltage drop≤1.8V, Normally open (L.on), normally closed (D.on)	Double output NPN	Single output PNP	Double output PNP
Switch type		Selectable L.on, D.on		
Indicator		Single output indicator (Red), dual output indicator (Orange)		
Display screen		7 segment 8 digit display (red: 4 digit, orange: 4 digit)		
Response time	15 μ s/22us(1-HS), 70 μ s(2-FS), 250 μ s(3-ST), 500 μ s(4-LG), 1ms(5-PL), 2ms(6-UL), 8ms(7-EL)			
ON/OFF Time delay function		ON delay, OFF delay, Single pulse output, ON + OFF delay, ON delay+Single pulse output 0.1~9.999ms		
Sensing distance		Thru-beam: 4000mm, Diffuse reflection: 1200mm		
Sensitivity adjustment		Teach-in / Manual		
External output function		Remote teach-in , Input stops once it shines, Syn trigger input, reset-input (for two outputs only)		
Operating temperature		-25°C~+55°C		
Operating humidity		35%~85%RH		
Ambient brightness		Sunlight≤10000lux, Incandescent lamp≤3000lux		
Anti-vibration		10~55Hz Double amplitude 1.5mm, XZY three directions, 2 hours each		
Shock resistance		50G(500m/S ²), XYZ three directions		
Degree of protection		IP50		
Material		Shell: PPE, Display: PC		
Connection method		2m 5 core cable		
Weight		50g		


Dimensions

Unit: mm



Circuit diagram

NPN



PNP

